



134101/2/3 NewTec CONO solo 50
 073381/2/3 NewTec CONO solo M
 072381/2/3 NewTec CONO solo S
 072301/2/3 NewTec CONO solo V



The installation may only be carried out by a qualified professional (e.g. electrician) who is familiar with the relevant regulations! Improper work not only endangers yourself, but also others!

Safety instructions

>Read the instructions carefully and keep them in a safe place. >Observe all warning notices and follow the instructions on this manual. >Do not install the device near heat sources and do not use it near water. >Do not allow metal objects or liquids to enter the device. They can lead to electric shock and defects. >Do not use chemical cleaning agents which can damage the paintwork. Only wipe the device with a dry cloth. >Only use additional devices recommended by NewTec Design: Audio GmbH. >Never repair the device or make changes to the device yourself. >In order to guarantee the optimal operating performance and service life of the device, use them in an operating environment that is within the temperature range 0-40 °C and humidity range 20-80%.

NewTec Design: Audio GmbH is in no way responsible for personal damage as a result of non-observance of the safety regulations and warnings. This also applies to consequential damage of any kind.

Montage

Remove the mounting bracket from the rear of the speaker by pulling below. Using the bracket, mark the two drilling points on the wall.

You can insert the screws either to the left or right of the cable outlet or above and below, depending on how the signal line is routed. Drill two holes in the wall. Mount this with the screws after inserting the wall plugs into the pre-drilled holes. The power cable already provided must go through the central hole of the bracket.

Connect the speaker cables according to the following markings of each model:

CONO solo 50:

Black = Minus pole (-); Red = Plus pole (+)

CONO solo M:

Black = Minus pole (-); Red = Plus pole (+)

CONO solo S:

Black = Minus pole (-); Red = Plus pole (+)

CONO solo V:

COM = Mass; 5W-10W-20W = Plus pole (+)

(Delivery state = 10W)

Tuck the cordgrip into the speaker socle and tilt the speaker 45° to the bracket and hook it into the slot. Connect the speaker by tilting it down into the bottom side of the bracket.

Technical Data	solo 50	solo M	solo S	solo V
Impedance	16 Ω	4 Ω	8 Ω	100V/1,9k-940-470 Ω
Nominal Power	50W/90W	50W/90W	100W/180W	5-10-20W
Frequency resp.	105Hz-21KHz	95Hz-21KHz	85Hz-21KHz	105-21KHz
Nominal Sens.	83,4dB	85,5dB	82,8dB	86,8dB
Max SPL	100dB	102dB	104dB	99,5dB
Dimensions	130x220mm	130x220mm	130x220mm	130x220mm
Weight	2,4kg	2,4kg	2,4kg	2,4kg